





# DC TO AC POWER INVERTER

AH SERIES PM-A-1000AH



Model No.	PM-A-1000AH-12	PM-A-1000AH-24
Output power continuous	1000W	1000W
Instant Surge	2000W	2000W
AC Output Voltage	100V/110V/115/120Vac or 220V/230V/240Vac	100V/110V/115/120Vac or 220V/230V/240Vac
Regulation	± 5%	± 5%
DC Input Voltage	10V~15VDC	20~30VDC
Output frequency	50Hz or 60Hz ± 3%	50Hz or 60Hz ± 3%
Low Battery Alarm & Shut-Down	10.5V ± 0.5VDC & 10V ± 0.5VDC	21V ± 0.8VDC & 20V ± 0.8VDC
Standby Current	<0.25A	<0.25A
Efficiency	> 85%	> 85%
Thermal Protect	50°C ± 5°C	50°C ± 5°C
Cooling	Auto Temperature Control Fan	Auto Temperature Control Fan
Protections	Input & Output Short circuit prot. High/Low Voltage Input Battery Low Alarm/ Shutdown Input/Output Isolated Over Load & Over Temperature Soft Start & AVR Design Remote Control Interface	Input & Output Short circuit prot. High/Low Voltage Input Battery Low Alarm/ Shutdown Input/Output Isolated Over Load & Over Temperature Soft Start & AVR Design Remote Control Interface
Fuse	30A X 5pcs	15A X 5pcs
AC Outlet	Alligator Clip	Alligator Clip
Dimensions (L x W x H)	340 * 249 * 93 mm	340 * 249 * 93 mm
Net weight (by Kg/s)	4.3	4.3
Output Waveform (Modified sine wave)		

**PLAN MY POWER (PTY) LTD**

[www.planmypower.co.za](http://www.planmypower.co.za)

email: [info@planmypower.co.za](mailto:info@planmypower.co.za)

Tel 0861 POWER1 , Tel +2711 678 7520

Fax : +27 11 678 6067