



DC TO AC POWER INVERTER

AH SERIES PM-A-0350AH



Model No.	PM-A-0350AH-12	PM-A-0350AH-24
Output power continuous	350W	350W
Instant Surge	700W	700W
AC Output Voltage	100V/110V/115V/120Vac or 220V/230V/240Vac	100V/110V/115V/120Vac or 220V/230V/240Vac
Regulation	± 5~10%	± 5~10%
DC Input Voltage	10~15V	20~30V
Low Battery Alarm & Shut-Down	10.5V ±0.5VDC & 10V ±0.5VDC	21V ±0.8VDC & 20V ±0.8VDC
Input Low Voltage Protection	Yes	Yes
Reverse Polarity Protection	Yes	Yes
Soft Start	Yes	Yes
DC/AC Isolated	Yes	Yes
AVR Design	Yes	Yes
Output Short Circuit Protection	Yes	Yes
Overload Protection	Yes	Yes
Auto Temperature Control Fan	Yes	Yes
Remote Control	No	No
Temperature protection	50°C ± 5°C	50°C ± 5°C
Output frequency	50Hz or 60Hz ± 3%	50Hz or 60Hz ± 3%
Efficiency	>85%	>85%
No Load Current	<0.25A	<0.25A
Dimensions (L x W x H mm)	190 * 102 * 63	190 * 102 * 63
Net weight (by Kg/s)	1.2	1.2
Accessory	Cigar Plug & Clip	Cigar Plug & Clip
Output Waveform (Modified sine wave)		

PLAN MY POWER (PTY) LTD

www.planmypower.co.za

email: info@planmypower.co.za

Tel 0861 POWER1 , Tel +2711 678 7520

Fax : +27 11 678 6067